

**Adaptor 1.0mm-Male to 1.0mm-Male****10M-10M+***Typical Performance Data*

FREQ.	INSERTION LOSS	1.0mm-MALE VSWR	1.0mm-MALE VSWR
(GHz)	(dB)	(:1)	(:1)
0.01	0.00	1.01	1.00
0.6	0.06	1.02	1.02
1.0	0.08	1.03	1.03
4.0	0.15	1.05	1.05
7.0	0.19	1.05	1.04
10.0	0.20	1.04	1.04
13.0	0.20	1.05	1.05
16.0	0.20	1.06	1.06
19.0	0.20	1.05	1.05
22.0	0.20	1.03	1.03
25.0	0.22	1.02	1.02
28.0	0.22	1.03	1.03
31.0	0.23	1.04	1.05
34.0	0.24	1.05	1.06
37.0	0.25	1.05	1.05
40.0	0.26	1.04	1.02
43.0	0.28	1.03	1.01
46.0	0.29	1.02	1.02
49.0	0.31	1.02	1.02
52.0	0.32	1.05	1.04
55.0	0.34	1.07	1.07
58.0	0.35	1.08	1.08
61.0	0.36	1.07	1.07
64.0	0.38	1.05	1.03
67.0	0.39	1.03	1.02
70.0	0.40	1.02	1.02
73.0	0.41	1.03	1.02
76.0	0.42	1.06	1.05
79.0	0.43	1.06	1.07
82.0	0.44	1.04	1.05
85.0	0.45	1.02	1.03
88.0	0.46	1.07	1.07
91.0	0.47	1.08	1.08
94.0	0.48	1.04	1.03
97.0	0.50	1.06	1.06
100.0	0.54	1.15	1.14
103.0	0.56	1.19	1.18
106.0	0.55	1.17	1.15
110.0	0.55	1.02	1.03



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site  
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: [www.minicircuits.com](http://www.minicircuits.com)



IF/RF MICROWAVE COMPONENTS