

Adaptor 1.35mm-Male to 1.35mm-Male**135M-135M+***Typical Performance Data*

FREQ.	INSERTION LOSS	1.35mm-MALE VSWR	1.35mm-MALE VSWR
(GHz)	(dB)	(:1)	(:1)
0.01	0.00	1.01	1.00
0.6	0.03	1.02	1.02
1.0	0.05	1.03	1.03
4.0	0.11	1.05	1.05
7.0	0.14	1.04	1.04
10.0	0.13	1.02	1.03
13.0	0.13	1.04	1.04
16.0	0.13	1.04	1.03
19.0	0.14	1.06	1.06
22.0	0.15	1.08	1.08
25.0	0.16	1.06	1.06
28.0	0.17	1.03	1.03
31.0	0.18	1.03	1.03
34.0	0.20	1.05	1.07
37.0	0.21	1.10	1.10
40.0	0.21	1.12	1.08
43.0	0.22	1.11	1.03
46.0	0.24	1.07	1.05
49.0	0.25	1.06	1.06
52.0	0.24	1.06	1.03
55.0	0.25	1.09	1.08
58.0	0.27	1.11	1.13
61.0	0.27	1.06	1.11
64.0	0.29	1.00	1.07
67.0	0.31	1.07	1.04
70.0	0.33	1.10	1.04
73.0	0.38	1.13	1.13
76.0	0.43	1.20	1.21
79.0	0.41	1.16	1.14
82.0	0.37	1.08	1.03
85.0	0.39	1.05	1.10
88.0	0.39	1.09	1.19
90.0	0.41	1.08	1.17



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com



IF/RF MICROWAVE COMPONENTS

REV. OR
 135M-135M+
 3/14/2024
 Page 1 of 1