

Typical Performance Data

FREQUENCY (MHz)								CONVERSION LOSS (dB)	RF IN = 0 dBm							
X1 OUTPUT	X2 OUTPUT	X3 OUTPUT	X4 OUTPUT	X5 OUTPUT	X6 OUTPUT	X7 OUTPUT	X8 OUTPUT		HARMONIC OUTPUT* (-dBc)							
X1 OUTPUT	X2 OUTPUT	X3 OUTPUT	X4 OUTPUT	X5 OUTPUT	X6 OUTPUT	X7 OUTPUT	X8 OUTPUT	X5 OUTPUT	X1 OUTPUT	X2 OUTPUT	X3 OUTPUT	X4 OUTPUT	X6 OUTPUT	X7 OUTPUT	X8 OUTPUT	
7.50	15.0	22.5	30.0	37.5	45.0	52.5	60.0	22.45	5.11	51.91	-1.40	44.41	45.68	7.26	51.16	
8.00	16.0	24.0	32.0	40.0	48.0	56.0	64.0	22.13	4.30	51.20	-2.21	44.26	46.39	7.68	53.11	
8.50	17.0	25.5	34.0	42.5	51.0	59.5	68.0	21.81	3.47	52.77	-2.90	46.44	49.17	8.03	56.27	
9.00	18.0	27.0	36.0	45.0	54.0	63.0	72.0	21.58	2.55	56.05	-3.59	50.48	53.89	8.42	61.44	
9.50	19.0	28.5	38.0	47.5	57.0	66.5	76.0	21.55	1.56	73.55	-4.30	73.05	72.21	8.78	76.10	
10.00	20.0	30.0	40.0	50.0	60.0	70.0	80.0	21.83	0.42	69.32	-5.08	60.02	61.46	9.24	65.77	
10.50	21.0	31.5	42.0	52.5	63.0	73.5	84.0	22.72	-1.29	62.25	-6.22	57.83	60.43	10.31	65.15	

* Harmonic Output below power level of X5 Output.



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site REV. OR



The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com

IF/RF MICROWAVE COMPONENTS

RMK-5-51+

7/6/2011

Page 1 of 2

Typical Performance Data

FREQUENCY (MHz)								CONVERSION LOSS (dB)	RF IN = +5 dBm							
X1 OUTPUT	X2 OUTPUT	X3 OUTPUT	X4 OUTPUT	X5 OUTPUT	X6 OUTPUT	X7 OUTPUT	X8 OUTPUT		HARMONIC OUTPUT* (-dBc)							
7.50	15.0	22.5	30.0	37.5	45.0	52.5	60.0	22.89	8.33	47.06	0.91	38.25	37.20	3.54	39.00	
8.00	16.0	24.0	32.0	40.0	48.0	56.0	64.0	22.51	7.61	46.79	0.22	38.28	37.87	4.07	40.07	
8.50	17.0	25.5	34.0	42.5	51.0	59.5	68.0	22.41	6.68	46.52	-0.56	38.45	38.69	4.65	41.32	
9.00	18.0	27.0	36.0	45.0	54.0	63.0	72.0	22.36	5.69	47.29	-1.35	39.74	40.62	5.17	43.59	
9.50	19.0	28.5	38.0	47.5	57.0	66.5	76.0	22.31	4.75	57.24	-2.05	50.82	53.61	5.50	56.53	
10.00	20.0	30.0	40.0	50.0	60.0	70.0	80.0	22.18	3.95	54.02	-2.62	48.61	50.65	5.63	52.87	
10.50	21.0	31.5	42.0	52.5	63.0	73.5	84.0	21.88	3.22	44.28	-3.14	38.45	40.91	5.64	43.53	

* Harmonic Output below power level of X5 Output.



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site REV. OR



The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com

IF/RF MICROWAVE COMPONENTS

RMK-5-51+

7/6/2011

Page 2 of 2