

# Flexible Coaxial Cable, SMA-M/N-M

# FL141-12SMNM+

## Typical Performance Data

FREQUENCY (MHz)	INSERTION LOSS (dB)	SMA-MALE RETURN LOSS (dB)	N-MALE RETURN LOSS (dB)
100	0.07	32.6	30.7
200	0.07	32.4	32.8
300	0.09	32.4	33.7
400	0.09	34.1	33.3
500	0.01	34.6	33.4
600	0.09	34.9	34.9
700	0.08	35.3	33.1
800	0.08	34.7	32.8
900	0.16	35.2	33.1
1000	0.10	35.6	33.0
1100	0.10	35.5	31.4
1250	0.15	35.7	31.3
1500	0.10	35.9	30.9
1750	0.12	37.3	31.3
2000	0.17	37.5	31.9
2001	0.17	36.1	31.3
2250	0.19	35.0	30.5
2500	0.19	33.9	30.2
2750	0.13	32.6	31.0
3000	0.13	31.6	31.2
3250	0.19	30.3	31.1
3500	0.20	29.3	31.2
3750	0.12	28.0	31.6
4000	0.18	26.6	31.3
4250	0.14	25.5	30.8
4500	0.12	24.5	31.3
5000	0.17	23.6	30.5
5500	0.30	23.5	31.2
6000	0.34	24.0	28.6
6500	0.25	27.5	29.2
7000	0.44	29.1	27.2
7500	0.56	29.7	26.9
8000	0.50	28.2	26.2
8500	0.40	27.0	24.1
9000	0.40	26.5	25.1
9500	0.19	25.5	24.5
10000	0.21	24.6	23.0
10500	0.42	25.3	25.0
11000	0.26	25.0	25.7
11500	0.26	24.6	26.3
12000	0.17	24.1	27.0
12500	0.28	23.3	27.1
13000	0.75	22.7	26.6
13500	0.47	23.2	27.2
14000	0.47	23.9	28.0
14500	0.39	24.8	29.7
15000	0.36	25.1	30.8
15500	0.46	25.0	31.2
16000	0.43	24.4	30.6
16500	0.69	23.5	28.8
17000	0.49	23.3	26.6
17500	0.79	23.0	23.0
18000	0.78	23.5	21.0



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site  
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: [www.minicircuits.com](http://www.minicircuits.com)



IF/RF MICROWAVE COMPONENTS

REV. OR  
 FL141-12SMNM+  
 5/10/2018  
 Page 1 of 1