

# Adaptor 1.0mm-Male to 1.85mm-Male

# 10M-185M+

## Typical Performance Data

FREQ.	INSERTION LOSS	1.0mm-MALE VSWR	1.85mm-MALE VSWR
(GHz)	(dB)	(:1)	(:1)
0.01	0.01	1.02	1.01
0.5	0.04	1.01	1.01
0.8	0.06	1.01	1.01
1.0	0.08	1.03	1.03
3.0	0.10	1.04	1.05
5.0	0.09	1.04	1.07
7.0	0.09	1.03	1.05
9.0	0.07	1.02	1.04
11.0	0.07	1.03	1.02
13.0	0.07	1.04	1.02
15.0	0.07	1.05	1.03
17.0	0.07	1.07	1.05
19.0	0.07	1.09	1.08
21.0	0.09	1.11	1.12
23.0	0.09	1.14	1.15
25.0	0.09	1.15	1.15
27.0	0.08	1.11	1.12
29.0	0.06	1.08	1.08
31.0	0.06	1.08	1.07
33.0	0.06	1.08	1.07
35.0	0.07	1.06	1.06
37.0	0.08	1.04	1.04
39.0	0.09	1.06	1.03
41.0	0.09	1.05	1.04
43.0	0.10	1.06	1.06
45.0	0.10	1.05	1.06
47.0	0.10	1.07	1.05
49.0	0.11	1.04	1.04
51.0	0.11	1.07	1.05
53.0	0.11	1.04	1.05
55.0	0.10	1.04	1.04
57.0	0.11	1.10	1.08
59.0	0.10	1.11	1.10
61.0	0.09	1.08	1.07
63.0	0.10	1.04	1.03
65.0	0.10	1.04	1.05
67.0	0.10	1.09	1.09



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site



The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: [www.minicircuits.com](http://www.minicircuits.com)

IF/RF MICROWAVE COMPONENTS

REV. OR  
10M-185M+  
3/27/2023  
Page 1 of 1