

Adapter, 1.85 mm-Female Right-Angle to 2.4 mm-Female

185FR-24F+

Typical Performance Data

FREQ.	INSERTION LOSS	1.85 mm-FEMALE VSWR	2.4 mm-FEMALE VSWR
(GHz)	(dB)	(:1)	(:1)
0	0.00	1.01	1.01
1	0.06	1.03	1.03
2	0.07	1.05	1.04
3	0.08	1.05	1.04
4	0.09	1.04	1.04
5	0.10	1.02	1.02
6	0.10	1.01	1.01
7	0.11	1.04	1.05
8	0.11	1.08	1.08
9	0.12	1.11	1.11
10	0.12	1.14	1.14
11	0.13	1.14	1.15
12	0.13	1.14	1.15
13	0.13	1.12	1.13
14	0.12	1.09	1.10
15	0.12	1.05	1.06
16	0.12	1.03	1.04
17	0.12	1.04	1.05
18	0.13	1.07	1.09
19	0.14	1.11	1.13
20	0.15	1.15	1.16
21	0.16	1.17	1.19
22	0.17	1.19	1.21
23	0.18	1.20	1.21
24	0.19	1.20	1.20
25	0.19	1.17	1.18
26	0.17	1.15	1.14
27	0.17	1.10	1.10
28	0.16	1.07	1.08
29	0.17	1.09	1.10
30	0.19	1.13	1.15
31	0.20	1.18	1.19
32	0.22	1.21	1.22
33	0.23	1.22	1.23
34	0.24	1.22	1.23
35	0.23	1.17	1.19
36	0.21	1.12	1.13
37	0.20	1.06	1.08
38	0.21	1.05	1.05
39	0.22	1.11	1.08
40	0.23	1.14	1.12
41	0.24	1.15	1.13
42	0.23	1.13	1.12
43	0.24	1.09	1.09
44	0.23	1.06	1.07
45	0.24	1.07	1.06
46	0.24	1.08	1.07
47	0.26	1.10	1.09
48	0.26	1.11	1.09
49	0.26	1.11	1.13
50	0.30	1.09	1.16



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com

IF/RF MICROWAVE COMPONENTS

REV. OR
185FR-24F+
10/21/2025
Page 1 of 1