

# Adapter, DIN-Female to DIN-Male

# DINF-DINM+

## Typical Performance Data

FREQ.	INSERTION LOSS	DIN-FEMALE VSWR	DIN-MALE VSWR
(GHz)	(dB)	(:1)	(:1)
0.01	0.00	1.00	1.00
0.04	0.00	1.00	1.00
0.07	0.00	1.00	1.00
0.10	0.00	1.00	1.00
0.15	0.00	1.00	1.00
0.20	0.00	1.00	1.01
0.25	0.00	1.01	1.01
0.30	0.00	1.01	1.01
0.35	0.00	1.01	1.01
0.40	0.00	1.01	1.01
0.45	0.00	1.01	1.01
0.50	0.00	1.01	1.01
0.55	0.00	1.01	1.01
0.60	0.01	1.01	1.01
0.70	0.01	1.01	1.01
0.80	0.01	1.02	1.01
0.90	0.01	1.02	1.01
1.00	0.01	1.02	1.01
1.10	0.01	1.02	1.02
1.20	0.01	1.02	1.02
1.30	0.01	1.02	1.02
1.40	0.01	1.03	1.02
1.50	0.01	1.03	1.02
1.60	0.01	1.03	1.02
1.70	0.01	1.03	1.02
1.80	0.01	1.03	1.02
1.90	0.01	1.03	1.02
2.00	0.01	1.03	1.02
2.10	0.01	1.03	1.02
2.20	0.01	1.03	1.02
2.30	0.01	1.03	1.02
2.40	0.01	1.03	1.02
2.50	0.01	1.03	1.02
2.60	0.01	1.03	1.02
2.70	0.01	1.03	1.02
2.80	0.01	1.03	1.01
2.90	0.01	1.03	1.01
3.00	0.00	1.03	1.01
3.50	0.01	1.02	1.01
4.00	0.01	1.02	1.01
4.50	0.01	1.02	1.02
5.00	0.00	1.02	1.02
6.00	0.01	1.03	1.04



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site



The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: [www.minicircuits.com](http://www.minicircuits.com)

IF/RF MICROWAVE COMPONENTS