

Adapter, DIN-Female Right Angle to DIN-Female DINFR-DINF+

Typical Performance Data

FREQ.	INSERTION LOSS	DIN-FEMALE VSWR	DIN-FEMALE VSWR
(GHz)	(dB)	(:1)	(:1)
0.01	0.00	1.00	1.00
0.04	0.00	1.00	1.00
0.07	0.00	1.00	1.00
0.10	0.01	1.01	1.01
0.15	0.01	1.01	1.01
0.20	0.01	1.01	1.01
0.25	0.02	1.01	1.01
0.30	0.02	1.01	1.01
0.35	0.02	1.02	1.01
0.40	0.02	1.02	1.02
0.45	0.02	1.02	1.02
0.50	0.03	1.02	1.02
0.55	0.03	1.02	1.02
0.60	0.03	1.02	1.02
0.70	0.03	1.03	1.02
0.80	0.03	1.03	1.02
0.90	0.03	1.03	1.02
1.00	0.03	1.03	1.02
1.10	0.03	1.04	1.03
1.20	0.04	1.04	1.03
1.30	0.04	1.04	1.03
1.40	0.04	1.04	1.03
1.50	0.04	1.04	1.03
1.60	0.04	1.05	1.03
1.70	0.04	1.05	1.03
1.80	0.04	1.05	1.03
1.90	0.04	1.05	1.03
2.00	0.04	1.06	1.03
2.10	0.04	1.06	1.04
2.20	0.04	1.06	1.04
2.30	0.04	1.06	1.04
2.40	0.04	1.07	1.04
2.50	0.04	1.07	1.04
2.60	0.04	1.07	1.04
2.70	0.04	1.08	1.04
2.80	0.04	1.08	1.05
2.90	0.04	1.08	1.05
3.00	0.04	1.09	1.05
3.50	0.04	1.10	1.06
4.00	0.05	1.12	1.07
4.50	0.05	1.14	1.10
5.00	0.05	1.14	1.12
6.00	0.05	1.15	1.15



P.O. Box 350166, Brooklyn, New York 11235-0003 • (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com

IF/RF MICROWAVE COMPONENTS

REV. OR
DINFR-DINF+
5/27/2026
Page 1 of 1