

Adapter, DIN-Male to DIN-Male

DINM-DINM+

Typical Performance Data

FREQ.	INSERTION LOSS	DIN-MALE VSWR	DIN-MALE VSWR
(GHz)	(dB)	(:1)	(:1)
0.01	0.00	1.00	1.00
0.04	0.00	1.00	1.00
0.07	0.00	1.00	1.00
0.10	0.00	1.00	1.00
0.15	0.00	1.00	1.00
0.20	0.00	1.00	1.00
0.25	0.00	1.00	1.00
0.30	0.00	1.00	1.00
0.35	0.00	1.00	1.00
0.40	0.00	1.00	1.00
0.45	0.00	1.00	1.00
0.50	0.00	1.00	1.00
0.55	0.00	1.00	1.00
0.60	0.00	1.00	1.00
0.70	0.00	1.00	1.00
0.80	0.00	1.00	1.00
0.90	0.00	1.00	1.00
1.00	0.00	1.00	1.00
1.10	0.00	1.00	1.01
1.20	0.00	1.01	1.01
1.30	0.00	1.01	1.01
1.40	0.00	1.01	1.01
1.50	0.00	1.01	1.01
1.60	0.01	1.01	1.01
1.70	0.01	1.01	1.01
1.80	0.01	1.01	1.01
1.90	0.00	1.01	1.02
2.00	0.01	1.02	1.02
2.10	0.01	1.02	1.02
2.20	0.01	1.02	1.02
2.30	0.01	1.02	1.02
2.40	0.01	1.02	1.03
2.50	0.01	1.02	1.03
2.60	0.01	1.03	1.03
2.70	0.01	1.03	1.03
2.80	0.01	1.03	1.03
2.90	0.01	1.04	1.04
3.00	0.01	1.04	1.04
3.50	0.01	1.05	1.05
4.00	0.01	1.06	1.06
4.50	0.02	1.08	1.07
5.00	0.02	1.09	1.09
6.00	0.03	1.12	1.12



P.O. Box 350166, Brooklyn, New York 11235-0003 • Fax (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com

IF/RF MICROWAVE COMPONENTS

REV. OR
DINM-DINM+
5/27/2026
Page 1 of 1