

Adapter, DIN-Male Right Angle to DIN-Male

DINMR-DINM+

Typical Performance Data

FREQ.	INSERTION LOSS	DIN-MALE VSWR	DIN-MALE VSWR
(GHz)	(dB)	(:1)	(:1)
0.01	0.00	1.00	1.00
0.04	0.00	1.00	1.00
0.07	0.00	1.01	1.01
0.10	0.00	1.01	1.01
0.15	0.01	1.01	1.01
0.20	0.01	1.01	1.01
0.25	0.01	1.01	1.02
0.30	0.01	1.02	1.02
0.35	0.02	1.02	1.02
0.40	0.02	1.02	1.02
0.45	0.02	1.02	1.02
0.50	0.02	1.03	1.02
0.55	0.02	1.03	1.03
0.60	0.02	1.03	1.03
0.70	0.03	1.04	1.03
0.80	0.03	1.04	1.04
0.90	0.03	1.04	1.04
1.00	0.03	1.05	1.04
1.10	0.03	1.05	1.04
1.20	0.03	1.05	1.04
1.30	0.03	1.06	1.04
1.40	0.04	1.06	1.05
1.50	0.04	1.06	1.05
1.60	0.04	1.06	1.05
1.70	0.04	1.07	1.05
1.80	0.04	1.07	1.05
1.90	0.04	1.07	1.05
2.00	0.04	1.07	1.05
2.10	0.04	1.08	1.06
2.20	0.04	1.08	1.06
2.30	0.04	1.08	1.06
2.40	0.04	1.08	1.06
2.50	0.04	1.09	1.06
2.60	0.04	1.09	1.06
2.70	0.04	1.09	1.06
2.80	0.04	1.09	1.06
2.90	0.04	1.09	1.06
3.00	0.04	1.09	1.06
3.50	0.04	1.09	1.06
4.00	0.04	1.09	1.07
4.50	0.05	1.09	1.08
5.00	0.05	1.11	1.11
6.00	0.07	1.15	1.16



P.O. Box 350166, Brooklyn, New York 11235-0003 • Fax (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com

IF/RF MICROWAVE COMPONENTS

REV. OR
DINMR-DINM+
5/27/2026
Page 1 of 1