

Adaptor 1.0mm-Male to 1.85mm-Female

10M-185F+

Typical Performance Data

FREQ.	INSERTION LOSS	1.0mm-MALE VSWR	1.85mm-FEMALE VSWR
(GHz)	(dB)	(:1)	(:1)
0.01	0.01	1.02	1.02
0.5	0.03	1.01	1.01
0.8	0.04	1.01	1.01
1.0	0.06	1.02	1.02
3.0	0.09	1.03	1.03
5.0	0.10	1.04	1.03
7.0	0.11	1.04	1.03
9.0	0.12	1.04	1.04
11.0	0.12	1.05	1.06
13.0	0.13	1.07	1.07
15.0	0.14	1.09	1.09
17.0	0.15	1.11	1.11
19.0	0.17	1.13	1.14
21.0	0.18	1.15	1.15
23.0	0.18	1.13	1.15
25.0	0.19	1.14	1.13
27.0	0.19	1.12	1.12
29.0	0.19	1.10	1.09
31.0	0.19	1.09	1.08
33.0	0.19	1.09	1.08
35.0	0.20	1.09	1.08
37.0	0.20	1.06	1.06
39.0	0.21	1.03	1.04
41.0	0.21	1.03	1.03
43.0	0.22	1.07	1.07
45.0	0.23	1.10	1.10
47.0	0.24	1.12	1.11
49.0	0.24	1.11	1.11
51.0	0.25	1.11	1.11
53.0	0.24	1.08	1.08
55.0	0.25	1.06	1.07
57.0	0.26	1.07	1.08
59.0	0.27	1.08	1.08
61.0	0.28	1.07	1.08
63.0	0.28	1.06	1.06
65.0	0.28	1.05	1.04
67.0	0.29	1.11	1.09



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site



The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com

IF/RF MICROWAVE COMPONENTS

REV. OR
10M-185F+
3/27/2023
Page 1 of 1