

# Adaptor 1.35mm-Female to 1.35mm-Male

# 135F-135M+

## Typical Performance Data

FREQ.	INSERTION LOSS	1.35mm-FEMALE VSWR	1.35mm-MALE VSWR
(GHz)	(dB)	(:1)	(:1)
0.01	0.00	1.01	1.01
0.6	0.04	1.03	1.02
1.0	0.06	1.03	1.03
4.0	0.10	1.05	1.05
7.0	0.13	1.05	1.06
10.0	0.13	1.03	1.05
13.0	0.14	1.04	1.02
16.0	0.15	1.04	1.01
19.0	0.16	1.05	1.03
22.0	0.16	1.05	1.06
25.0	0.18	1.08	1.07
28.0	0.17	1.07	1.07
31.0	0.18	1.04	1.06
34.0	0.19	1.05	1.02
37.0	0.19	1.06	1.02
40.0	0.22	1.10	1.05
43.0	0.24	1.14	1.08
46.0	0.25	1.18	1.10
49.0	0.26	1.16	1.10
52.0	0.26	1.08	1.10
55.0	0.27	1.07	1.07
58.0	0.27	1.04	1.04
61.0	0.28	1.02	1.02
64.0	0.29	1.05	1.05
67.0	0.31	1.07	1.07
70.0	0.34	1.13	1.12
73.0	0.34	1.13	1.08
76.0	0.35	1.19	1.11
79.0	0.34	1.20	1.09
82.0	0.35	1.13	1.09
85.0	0.36	1.09	1.10
88.0	0.37	1.07	1.09
90.0	0.38	1.06	1.07



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site  
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: [www.minicircuits.com](http://www.minicircuits.com)



IF/RF MICROWAVE COMPONENTS