

Adapter, SMA-Female to SMA-Male

SF-MQK50+

Typical Performance Data

| FREQUENCY (MHz) | INSERTION LOSS (dB) | SMA-FEMALE RETURN LOSS (dB) | SMA-MALE RETURN LOSS (dB) |
|--------------------|------------------------|-----------------------------------|---------------------------------|
| 10 | 0.01 | 46.06 | 46.06 |
| 50 | 0.01 | 46.06 | 46.06 |
| 100 | 0.02 | 46.06 | 46.06 |
| 500 | 0.03 | 46.06 | 46.06 |
| 900 | 0.04 | 46.06 | 40.09 |
| 1000 | 0.04 | 40.09 | 40.09 |
| 2000 | 0.05 | 36.61 | 36.61 |
| 3000 | 0.06 | 32.26 | 32.26 |
| 4000 | 0.06 | 30.71 | 30.71 |
| 5000 | 0.07 | 29.42 | 29.42 |
| 6000 | 0.07 | 29.42 | 29.42 |
| 7000 | 0.07 | 29.42 | 28.30 |
| 8000 | 0.08 | 28.30 | 27.32 |
| 9000 | 0.09 | 26.44 | 25.66 |
| 10000 | 0.10 | 24.29 | 23.69 |
| 12000 | 0.09 | 24.29 | 23.69 |
| 13000 | 0.15 | 24.29 | 23.69 |
| 15000 | 0.12 | 24.29 | 23.69 |
| 16000 | 0.13 | 24.29 | 23.69 |
| 18000 | 0.18 | 24.29 | 23.69 |

REV. X1
SF-MQK50+
061114
Page 1 of 1



IF/RF MICROWAVE COMPONENTS • ISO 9001 ISO 14001 AS 9100 CERTIFIED RoHS compliant
P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661



The Design Engineers Search Engine finds the model you need, Instantly • For detailed performance specs & shopping online see

