

Adaptor 2.92mm-Male to 3.5mm-Female

KM-35F+

Typical Performance Data

FREQ.	INSERTION LOSS	2.92mm-MALE VSWR	3.5mm-FEMALE VSWR
(GHz)	(dB)	(:1)	(:1)
0.01	0.01	1.01	1.01
0.1	0.01	1.01	1.01
1.0	0.03	1.01	1.01
2.0	0.03	1.02	1.02
3.0	0.04	1.02	1.02
4.0	0.05	1.02	1.03
5.0	0.05	1.04	1.03
6.0	0.06	1.04	1.03
7.0	0.06	1.04	1.04
8.0	0.06	1.04	1.04
9.0	0.07	1.04	1.04
10.0	0.07	1.05	1.04
11.0	0.07	1.04	1.04
12.0	0.08	1.04	1.04
13.0	0.08	1.05	1.04
14.0	0.08	1.04	1.04
15.0	0.09	1.04	1.04
16.0	0.09	1.04	1.04
17.0	0.09	1.04	1.04
18.0	0.10	1.05	1.04
19.0	0.10	1.04	1.04
20.0	0.11	1.05	1.04
21.0	0.11	1.07	1.04
22.0	0.11	1.04	1.04
23.0	0.11	1.04	1.04
24.0	0.12	1.04	1.03
25.0	0.12	1.02	1.02
26.0	0.13	1.02	1.02
27.0	0.13	1.02	1.03
28.0	0.13	1.03	1.04
29.0	0.14	1.04	1.05
30.0	0.14	1.06	1.07
31.0	0.15	1.05	1.07
32.0	0.15	1.07	1.07
33.0	0.16	1.07	1.08



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com



IF/RF MICROWAVE COMPONENTS