

Coaxial SMA Band Pass Filter

VBFZ-1690+

Typical Performance Data

FREQUENCY (MHz)	INSERTION LOSS (dB)	RETURN LOSS (dB)
10	86.61	0.00
80	73.10	0.01
250	64.79	0.03
860	32.45	0.30
930	27.04	0.37
1095	15.22	0.81
1222	7.44	2.28
1323	3.21	6.43
1455	1.45	19.16
1690	1.31	18.02
1925	1.61	13.64
2152	2.95	11.48
2226	5.12	8.06
2305	11.33	3.51
2380	20.83	1.89
2460	36.26	1.33
2600	33.24	1.07
5000	59.51	0.76
9000	28.16	0.72
12000	19.23	4.22

REV. X1
VBFZ-1690+
070207
Page 1 of 1



IF/RF MICROWAVE COMPONENTS • ISO 9001 ISO 14001 AS 9100 CERTIFIED RoHS compliant
P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661



The Design Engineers Search Engine finds the model you need, Instantly • For detailed performance specs & shopping online see

