

Coaxial Low Pass Filter

BLP-1000+

Typical Performance Data

FREQUENCY (MHz)	INSERTION LOSS (dB)	RETURN LOSS (dB)	FREQUENCY (MHz)	GROUP DELAY (nsec)
10.0	0.00	40.90	10.0	0.800
82.5	0.00	28.40	82.5	0.800
305.0	0.10	24.50	157.5	0.900
525.0	0.20	20.00	230.0	0.800
747.5	0.50	12.20	305.0	0.900
900.0	0.40	23.80	377.5	0.900
930.0	0.80	12.40	452.5	0.900
970.0	2.10	5.90	525.0	1.000
990.0	3.10	4.10	600.0	0.900
1115.0	12.80	0.60	672.5	1.000
1250.0	23.30	0.20	747.5	1.200
1270.0	24.80	0.20	820.0	1.400
1280.0	25.50	0.20	900.0	1.800
1300.0	27.10	0.20	930.0	2.100
1340.0	30.20	0.20	950.0	2.000
1400.0	34.90	0.20	970.0	1.900
1500.0	43.30	0.20	990.0	2.000
1550.0	48.00	0.10	1115.0	1.100
1600.0	53.10	0.20	1190.0	0.800
1700.0	61.90	0.20	1250.0	1.000
1750.0	58.50	0.10	1270.0	0.800
1760.1	58.60	0.10	1280.0	0.300
1790.0	57.20	0.10	1300.0	1.000
1800.0	56.80	0.10	1340.0	0.500
1820.0	55.80	0.10	1400.0	0.800
1850.0	54.80	0.10	1500.0	0.200
1860.0	53.90	0.10	1550.0	0.800
1880.0	53.20	0.10	1600.0	0.500
1900.1	52.60	0.10	1700.0	0.400
1950.0	50.30	0.10	1750.0	0.400

REV. X1
BLP-1000+
060724
Page 1 of 1



IF/RF MICROWAVE COMPONENTS • ISO 9001 ISO 14001 AS 9100 CERTIFIED • RoHS compliant
P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661



The Design Engineers Search Engine finds the model you need, Instantly • For detailed performance specs & shopping online see

