

# Surface Mount Band Pass Filter

# BPF-EDU2005

## Typical Performance Data

FREQUENCY (MHz)	INSERTION LOSS (dB)	RETURN LOSS (dB)
1.0	99.07	0.03
10.0	117.98	0.01
20.0	97.74	0.01
30.0	84.68	0.01
40.0	65.51	0.02
54.0	33.56	0.14
55.0	29.83	0.20
57.0	20.28	0.62
58.0	13.88	1.53
59.0	7.08	5.70
60.0	4.36	23.27
60.0	4.35	24.18
60.1	4.35	24.09
61.0	6.69	5.96
64.0	21.29	0.42
67.0	29.05	0.14
68.0	30.83	0.11
100.0	46.98	0.02
150.0	51.64	0.04
200.0	56.01	0.07
260.0	65.10	0.11
300.0	59.03	0.13
310.0	57.41	0.14
320.0	56.02	0.14

FREQUENCY (MHz)	GROUP DELAY (nsec)
59.95	200.95
60	200.43
60.05	199.93



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site  
Provides ACTUAL Data Instantly From MINI-CIRCUITS At: [www.minicircuits.com](http://www.minicircuits.com)



The Design Engineers Search Engine

IF/RF MICROWAVE COMPONENTS

REV. X1  
BPF-EDU2005  
URJ  
151130  
Page 1 of 1