

# Coaxial Low Pass Filter (Flat Time Delay)

# NBLP-117+

## Typical Performance Data

FREQUENCY (MHz)	INSERTION LOSS (dB)	RETURN LOSS (dB)	FREQUENCY (MHz)	GROUP DELAY (nsec)
1.0	0.02	35.30	1.0	3.075
23.0	0.15	16.80	12.0	3.015
33.0	0.26	13.80	23.0	3.252
44.0	0.42	11.50	33.0	3.331
55.0	0.65	9.60	44.0	3.126
65.0	0.90	8.30	55.0	3.140
66.0	0.92	8.20	65.0	3.044
100.0	1.96	4.80	66.0	3.271
117.0	2.80	3.50	83.0	3.303
118.0	2.86	3.50	100.0	3.348
152.0	5.63	1.90	117.0	3.233
185.0	8.79	1.20	118.0	3.593
201.0	10.40	0.90	135.0	3.409
218.0	12.20	0.70	152.0	2.782
234.0	13.99	0.50	168.0	2.798
235.0	14.10	0.50	185.0	2.689
257.0	16.54	0.30	201.0	2.681
279.0	18.92	0.30	218.0	2.252
290.0	20.08	0.20	234.0	2.060
301.0	21.23	0.20	235.0	2.038
312.0	22.36	0.20	246.0	1.965
313.0	22.46	0.20	257.0	1.759
361.0	27.82	0.20	268.0	1.562
409.0	32.27	0.20	279.0	1.358
457.0	35.79	0.20	290.0	1.372
505.0	39.52	0.20	301.0	1.483
529.0	41.10	0.20	312.0	1.659
553.0	42.74	0.20	313.0	1.765
577.0	44.30	0.30	337.0	1.324
600.0	45.95	0.30	361.0	1.555

REV. X1  
NBLP-117+  
060724  
Page 1 of 1



IF/RF MICROWAVE COMPONENTS • ISO 9001 ISO 14001 AS 9100 CERTIFIED • RoHS compliant  
P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661



The Design Engineers Search Engine finds the model you need, Instantly • For detailed performance specs & shopping online see

