

Coaxial Low Pass Filter (Flat Time Delay)

NBLP-200+

Typical Performance Data

FREQUENCY (MHz)	INSERTION LOSS (dB)	RETURN LOSS (dB)	FREQUENCY (MHz)	GROUP DELAY (nsec)
1.0	0.04	35.50	1.0	1.829
41.0	0.10	27.00	21.0	1.915
61.0	0.16	20.60	41.0	2.140
81.0	0.22	16.60	61.0	2.006
101.0	0.33	13.40	81.0	2.109
120.0	0.52	10.40	101.0	2.087
121.0	0.53	10.20	120.0	2.170
174.0	2.10	4.70	121.0	2.113
200.0	3.22	3.50	148.0	2.521
201.0	3.26	3.50	174.0	2.169
258.0	6.65	1.60	200.0	1.964
315.0	9.45	0.90	201.0	2.367
344.0	11.17	0.70	230.0	1.912
372.0	13.45	0.50	258.0	1.485
400.0	15.58	0.40	287.0	1.356
401.0	15.65	0.40	315.0	2.048
439.0	17.90	0.30	344.0	2.142
477.0	20.36	0.30	372.0	1.206
496.0	21.60	0.20	400.0	0.894
515.0	22.72	0.20	401.0	1.205
534.0	23.75	0.20	420.0	1.143
535.0	23.81	0.20	439.0	0.984
580.0	26.67	0.20	458.0	1.412
624.0	29.26	0.20	477.0	0.888
668.0	31.05	0.20	496.0	0.903
712.0	33.19	0.30	515.0	1.244
734.0	34.36	0.30	534.0	1.282
756.0	35.72	0.30	535.0	0.796
778.0	37.00	0.30	558.0	1.491
800.0	37.94	0.30	580.0	0.941

REV. X1
NBLP-200+
060724
Page 1 of 1



IF/RF MICROWAVE COMPONENTS • ISO 9001 ISO 14001 AS 9100 CERTIFIED • RoHS compliant
P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661



The Design Engineers Search Engine finds the model you need, Instantly • For detailed performance specs & shopping online see

