

# Hand-Flex Coaxial Cable, Right Angle SMA-M/SMA-F Bulkhead 086-4SBSMR+

## Typical Performance Data

FREQUENCY (MHz)	INSERTION LOSS (dB)	RIGHT ANGLE SMA-MALE RETURN LOSS (dB)	SMA-FEMALE BULKHEAD RETURN LOSS (dB)
100.0	0.04	46.6	51.2
200.0	0.07	44.2	55.7
400.0	0.11	39.9	50.0
500.0	0.12	38.7	43.2
600.0	0.12	37.8	39.4
700.0	0.13	37.1	37.0
800.0	0.14	36.8	35.7
900.0	0.15	36.8	35.1
1000.0	0.15	36.9	35.3
1100.0	0.16	36.9	36.0
1250.0	0.16	36.0	37.1
1500.0	0.17	33.6	34.0
1750.0	0.19	32.3	30.7
2000.0	0.20	32.2	30.1
2250.0	0.20	31.6	31.3
2500.0	0.22	30.3	30.5
2750.0	0.22	30.1	28.6
3000.0	0.23	31.6	28.6
3250.0	0.23	31.9	30.0
3500.0	0.24	30.0	29.7
3750.0	0.25	30.5	29.2
4000.0	0.25	35.2	31.8
4250.0	0.25	33.4	32.9
4500.0	0.26	28.5	28.9
5000.0	0.27	40.1	35.6
5500.0	0.28	26.7	28.1
6000.0	0.28	37.7	36.1
6500.0	0.30	23.4	24.1
7000.0	0.29	33.6	34.9
7500.0	0.33	21.8	21.9
8000.0	0.32	26.4	26.6
8500.0	0.34	22.2	22.2
9000.0	0.34	22.4	22.5
9500.0	0.33	25.9	25.4
10000.0	0.35	21.6	21.6
10500.0	0.33	29.9	30.2
11000.0	0.36	22.8	22.9
11500.0	0.34	33.5	34.3
12000.0	0.35	27.9	27.8
12500.0	0.35	33.4	34.7
13000.0	0.35	41.9	42.0
13500.0	0.36	39.9	42.7
14000.0	0.37	31.2	32.0
14500.0	0.38	34.4	34.1
15000.0	0.40	26.9	26.9
15500.0	0.40	31.4	32.1
16000.0	0.43	24.4	24.5
16500.0	0.41	28.3	29.4
17000.0	0.47	21.6	21.9
17500.0	0.44	26.8	27.6
18000.0	0.51	20.0	20.1



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site



The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: [www.minicircuits.com](http://www.minicircuits.com)

IF/RF MICROWAVE COMPONENTS

REV. OR  
086-4SBSMR+  
3/26/2014

Page 1 of 1