

# Adaptor 2.4mm-Female to 3.5mm-Female

# 24F-35F+

## Typical Performance Data

FREQ.	INSERTION LOSS	2.4mm-FEMALE VSWR	3.5mm-FEMALE VSWR
(GHz)	(dB)	(:1)	(:1)
0.01	0.00	1.02	1.01
0.10	0.01	1.00	1.00
0.20	0.02	1.01	1.00
0.30	0.02	1.01	1.01
0.40	0.02	1.01	1.01
0.50	0.02	1.01	1.01
0.60	0.03	1.01	1.01
0.70	0.03	1.01	1.01
0.80	0.03	1.01	1.01
1.00	0.03	1.01	1.02
2.00	0.03	1.02	1.03
3.00	0.04	1.03	1.03
4.00	0.05	1.03	1.03
5.00	0.05	1.03	1.04
6.00	0.05	1.04	1.03
7.00	0.06	1.03	1.02
8.00	0.06	1.02	1.02
9.00	0.06	1.02	1.02
10.00	0.07	1.02	1.02
11.00	0.07	1.03	1.04
12.00	0.07	1.04	1.05
13.00	0.08	1.04	1.05
14.00	0.08	1.04	1.06
15.00	0.09	1.04	1.05
16.00	0.10	1.04	1.04
17.00	0.10	1.05	1.04
18.00	0.11	1.05	1.06
19.00	0.11	1.06	1.05
20.00	0.12	1.08	1.08
21.00	0.13	1.10	1.10
22.00	0.13	1.10	1.08
23.00	0.13	1.08	1.08
24.00	0.13	1.08	1.10
25.00	0.14	1.11	1.10
26.00	0.14	1.14	1.12
27.00	0.15	1.16	1.17
28.00	0.15	1.18	1.20
29.00	0.16	1.20	1.20
30.00	0.17	1.21	1.22
31.00	0.17	1.18	1.20
32.00	0.16	1.14	1.14
33.00	0.15	1.08	1.09
34.50	0.15	1.07	1.04



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site  
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: [www.minicircuits.com](http://www.minicircuits.com)



IF/RF MICROWAVE COMPONENTS