

Adaptor 2.4mm-Female to 3.5mm-Male**24F-35M+***Typical Performance Data*

FREQ.	INSERTION LOSS	2.4mm-FEMALE VSWR	3.5mm-MALE VSWR
(GHz)	(dB)	(:1)	(:1)
0.01	0.00	1.01	1.01
0.10	0.01	1.01	1.01
0.20	0.01	1.01	1.01
0.30	0.01	1.00	1.01
0.40	0.02	1.01	1.01
0.50	0.02	1.01	1.01
0.60	0.02	1.01	1.01
0.70	0.03	1.01	1.01
0.80	0.02	1.01	1.01
1.00	0.03	1.01	1.01
2.00	0.03	1.02	1.02
3.00	0.04	1.02	1.02
4.00	0.04	1.02	1.02
5.00	0.05	1.02	1.03
6.00	0.05	1.02	1.03
7.00	0.05	1.02	1.03
8.00	0.06	1.03	1.03
9.00	0.06	1.03	1.04
10.00	0.06	1.04	1.04
11.00	0.06	1.04	1.04
12.00	0.07	1.05	1.05
13.00	0.07	1.05	1.05
14.00	0.07	1.05	1.05
15.00	0.07	1.04	1.04
16.00	0.08	1.03	1.04
17.00	0.09	1.03	1.04
18.00	0.09	1.01	1.03
19.00	0.10	1.00	1.03
20.00	0.11	1.01	1.02
21.00	0.10	1.02	1.02
22.00	0.09	1.02	1.02
23.00	0.10	1.03	1.03
24.00	0.12	1.03	1.03
25.00	0.15	1.03	1.04
26.00	0.09	1.03	1.04
27.00	0.11	1.03	1.04
28.00	0.13	1.03	1.04
29.00	0.13	1.04	1.04
30.00	0.12	1.05	1.04
31.00	0.13	1.06	1.04
32.00	0.14	1.07	1.03
33.00	0.15	1.07	1.02
34.50	0.16	1.07	1.01



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com



IF/RF MICROWAVE COMPONENTS

REV. OR
24F-35M+
8/14/2025
Page 1 of 1