

Adaptor 2.4mm-Male to 3.5mm-Male**24M-35M+***Typical Performance Data*

FREQ.	INSERTION LOSS	2.4mm-MALE VSWR	3.5mm-MALE VSWR
(GHz)	(dB)	(:1)	(:1)
0.01	0.01	1.01	1.01
0.10	0.00	1.01	1.01
0.20	0.01	1.01	1.01
0.30	0.01	1.01	1.01
0.40	0.01	1.01	1.01
0.50	0.02	1.01	1.01
0.60	0.02	1.01	1.01
0.70	0.02	1.01	1.01
0.80	0.02	1.01	1.01
1.00	0.03	1.01	1.01
2.00	0.03	1.02	1.02
3.00	0.04	1.02	1.02
4.00	0.04	1.02	1.03
5.00	0.05	1.03	1.04
6.00	0.05	1.04	1.04
7.00	0.06	1.04	1.04
8.00	0.06	1.03	1.03
9.00	0.06	1.01	1.02
10.00	0.07	1.02	1.00
11.00	0.07	1.03	1.02
12.00	0.08	1.03	1.04
13.00	0.08	1.03	1.05
14.00	0.08	1.04	1.06
15.00	0.09	1.05	1.06
16.00	0.10	1.05	1.04
17.00	0.10	1.04	1.02
18.00	0.10	1.06	1.05
19.00	0.11	1.08	1.08
20.00	0.12	1.11	1.10
21.00	0.12	1.10	1.12
22.00	0.11	1.10	1.13
23.00	0.11	1.06	1.10
24.00	0.12	1.04	1.07
25.00	0.14	1.08	1.07
26.00	0.15	1.10	1.09
27.00	0.16	1.07	1.12
28.00	0.16	1.07	1.15
29.00	0.17	1.13	1.16
30.00	0.18	1.19	1.15
31.00	0.18	1.21	1.14
32.00	0.17	1.18	1.11
33.00	0.17	1.08	1.08
34.50	0.19	1.03	1.04



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com



IF/RF MICROWAVE COMPONENTS

REV. OR
24M-35M+
8/14/2025
Page 1 of 1