

Adaptor 2.4mm-Male to 2.92mm-Male**24M-KM+***Typical Performance Data*

FREQ.	INSERTION LOSS	2.4mm-MALE VSWR	2.92mm-MALE VSWR
(GHz)	(dB)	(:1)	(:1)
0.01	0.02	1.01	1.01
0.05	0.01	1.00	1.01
0.10	0.01	1.00	1.01
1.00	0.02	1.01	1.02
2.00	0.03	1.01	1.02
3.00	0.03	1.01	1.02
4.00	0.04	1.02	1.02
5.00	0.04	1.03	1.03
6.00	0.05	1.04	1.05
7.00	0.05	1.05	1.07
8.00	0.06	1.06	1.08
9.00	0.05	1.06	1.09
10.00	0.05	1.05	1.08
11.00	0.06	1.04	1.06
12.00	0.06	1.04	1.03
13.00	0.06	1.06	1.02
14.00	0.07	1.08	1.05
15.00	0.08	1.10	1.09
16.00	0.08	1.10	1.12
17.00	0.08	1.10	1.14
18.00	0.07	1.09	1.15
19.00	0.08	1.07	1.13
20.00	0.09	1.07	1.09
21.00	0.09	1.08	1.07
22.00	0.08	1.09	1.09
23.00	0.09	1.09	1.11
24.00	0.11	1.09	1.12
25.00	0.11	1.07	1.12
26.00	0.11	1.06	1.11
27.00	0.11	1.04	1.08
28.00	0.11	1.02	1.06
29.00	0.11	1.02	1.04
30.00	0.10	1.02	1.04
31.00	0.10	1.03	1.05
32.00	0.10	1.05	1.05
33.00	0.11	1.08	1.06
34.00	0.13	1.11	1.06
35.00	0.14	1.12	1.05
36.00	0.13	1.12	1.06
37.00	0.10	1.12	1.09
38.00	0.11	1.12	1.10
39.00	0.12	1.13	1.10
40.00	0.12	1.15	1.09



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com



IF/RF MICROWAVE COMPONENTS

REV. OR
24M-KM+
7/18/2025
Page 1 of 1