

Non-Magnetic Flex Cable SMA Male to SMA Male

86N-50CSM

Typical Performance Data

FREQ.	INSERTION LOSS	SMA MALE RETURN LOSS IN	SMA MALE RETURN LOSS OUT
(GHz)	(dB)	(dB)	(dB)
0	0.03	46.07	47.49
1	0.32	45.33	47.43
2	0.46	42.45	42.34
3	0.58	41.19	42.54
4	0.68	39.10	38.42
5	0.77	40.00	38.92
6	0.85	38.85	39.04
7	0.93	36.83	37.91
8	1.00	34.45	35.16
9	1.07	35.41	35.63
10	1.14	27.01	27.14
11	1.21	25.01	25.26
12	1.27	28.73	29.81
13	1.33	32.49	33.72
14	1.39	35.13	34.95
15	1.45	32.15	33.02
16	1.51	26.89	27.73
17	1.57	24.58	25.74
18	1.62	26.26	27.20

