

Phase-Stable Flexible Cable SMA Male to SMA Male

CBN-3.5FT-SMSM+

Typical Performance Data

FREQ.	INSERTION LOSS	SMA MALE RETURN LOSS IN	SMA MALE RETURN LOSS OUT
(GHz)	(dB)	(dB)	(dB)
0	0.04	35.59	35.51
1	0.29	37.91	37.49
2	0.51	40.65	39.68
3	0.67	34.18	34.33
4	0.80	40.95	42.47
5	0.92	33.78	35.72
6	1.02	33.86	34.63
7	1.12	39.13	39.97
8	1.21	37.25	37.69
9	1.29	36.82	37.74
10	1.37	35.21	36.81
11	1.45	36.31	36.61
12	1.52	38.07	38.84
13	1.59	37.49	37.83
14	1.66	34.75	35.64
15	1.73	33.40	33.94
16	1.80	29.76	30.32
17	1.86	29.42	30.51
18	1.91	30.70	33.44
19	1.99	27.17	27.67
20	2.04	27.10	28.91
21	2.10	28.36	33.37
22	2.17	24.68	25.90
23	2.22	24.54	25.31
24	2.27	28.79	29.23
25	2.33	25.52	25.39
26	2.37	26.16	26.63
27	2.42	32.79	30.33



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com

IF/RF MICROWAVE COMPONENTS

REV. OR
 CBN-3.5FT-SMSM+
 4/24/2025
 Page 1 of 1