

Bi-Directional Coupler

CPL-20-14+

Typical Performance Data

FREQ. (MHz)	INSERTION LOSS (dB)	COUPLING (dB)		DIRECTIVITY (dB)		RETURN LOSS (dB)			
		IN-FWD	OUT-REV	IN-REV	OUT-FWD	IN	OUT	FWD	REV
9000.0	0.21	19.37	19.32	15.33	15.13	25.09	22.32	18.05	17.85
9200.0	0.19	19.26	19.17	15.43	15.45	27.34	26.37	19.69	20.62
9300.0	0.19	19.22	19.13	15.72	16.24	28.16	29.06	20.19	21.18
9400.0	0.18	19.20	19.11	16.60	17.30	31.52	30.18	21.20	20.96
9500.0	0.17	19.18	19.09	16.32	17.20	42.44	35.39	22.69	20.89
9600.0	0.17	19.16	19.07	16.17	17.10	38.46	38.63	25.36	22.45
9700.0	0.18	19.17	19.08	16.53	17.60	47.88	36.90	32.19	27.25
9800.0	0.18	19.19	19.10	17.05	18.33	38.96	34.26	33.04	36.99
9900.0	0.18	19.20	19.12	17.63	19.31	40.41	33.03	38.52	39.66
10000.0	0.18	19.21	19.15	16.95	18.84	30.04	27.12	28.74	26.96
10100.0	0.19	19.22	19.19	16.45	18.16	26.51	23.70	25.17	23.38
10200.0	0.20	19.25	19.25	16.51	18.10	25.80	22.27	20.49	19.19
10300.0	0.20	19.27	19.32	16.24	18.08	24.36	21.73	20.71	20.70
10400.0	0.21	19.27	19.36	15.80	18.16	21.57	21.48	21.21	21.96
10500.0	0.21	19.26	19.40	15.11	17.60	19.40	20.28	19.58	19.80
10650.0	0.21	19.24	19.45	14.59	17.32	19.15	19.61	17.35	17.58
10800.0	0.22	19.24	19.51	14.51	17.37	21.14	18.85	16.36	15.24
10950.0	0.23	19.25	19.57	14.06	17.02	19.68	17.25	15.23	13.68
11100.0	0.23	19.24	19.63	13.00	15.96	17.91	16.58	14.43	13.06



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com



IF/RF MICROWAVE COMPONENTS

REV. OR
CPL-20-14+
9/11/2014
Page 1 of 1