

Coaxial Fixed Attenuator

FW-12A+

Typical Performance Data

FREQ.	ATTENUATION	VSWR
(MHz)	(dB)	(:1)
10	11.98	1.16
20	11.99	1.16
50	11.99	1.16
100	11.99	1.16
200	12.00	1.16
300	12.01	1.16
400	12.02	1.16
500	12.03	1.16
600	12.04	1.16
700	12.05	1.16
800	12.06	1.17
900	12.07	1.17
1000	12.08	1.17
1200	12.09	1.17
1400	12.10	1.17
1600	12.12	1.17
1800	12.14	1.17
2000	12.15	1.17
2200	12.17	1.17
2400	12.18	1.17
2600	12.20	1.17
2800	12.21	1.16
3000	12.23	1.16
3200	12.24	1.16
3400	12.25	1.15
3600	12.27	1.14
3800	12.28	1.14
4000	12.30	1.13
4200	12.32	1.13
4400	12.33	1.12
4600	12.35	1.12
4800	12.37	1.12
5000	12.39	1.11
5200	12.41	1.11
5400	12.43	1.11
5600	12.45	1.11
5800	12.47	1.11
6000	12.49	1.11
6200	12.51	1.11
6400	12.53	1.11
6600	12.54	1.11
6800	12.56	1.10
7000	12.58	1.10
7200	12.60	1.09
7400	12.62	1.09
7600	12.64	1.08
7800	12.65	1.07
8000	12.67	1.06
8200	12.69	1.06
8400	12.70	1.05
8600	12.71	1.05
8800	12.73	1.06
9000	12.74	1.06
9200	12.75	1.07
9400	12.76	1.08
9600	12.77	1.09
10000	12.79	1.12
11000	12.82	1.16
11500	12.82	1.16
12000	12.83	1.16



ISO 9001 ISO 14001 AS 9100 CERTIFIED



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com



IF/RF MICROWAVE COMPONENTS

REV. OR
FW-12A+
211119
Page 1 of 1