

Coaxial Fixed Attenuator

FW-4A+

Typical Performance Data

FREQ.	ATTENUATION	VSWR
(MHz)	(dB)	(:1)
10	3.92	1.13
20	3.92	1.13
50	3.93	1.13
100	3.93	1.13
200	3.95	1.13
300	3.96	1.12
400	3.97	1.12
500	3.98	1.12
600	3.99	1.12
700	4.00	1.12
800	4.01	1.11
900	4.02	1.11
1000	4.03	1.11
1200	4.05	1.11
1400	4.06	1.11
1600	4.07	1.11
1800	4.09	1.10
2000	4.10	1.10
2200	4.11	1.10
2400	4.11	1.10
2600	4.12	1.10
2800	4.13	1.10
3000	4.14	1.10
3200	4.14	1.10
3400	4.15	1.10
3600	4.16	1.11
3800	4.16	1.11
4000	4.16	1.11
4200	4.17	1.12
4400	4.18	1.12
4600	4.18	1.12
4800	4.19	1.13
5000	4.19	1.13
5200	4.20	1.14
5400	4.21	1.14
5600	4.22	1.14
5800	4.22	1.14
6000	4.23	1.15
6200	4.24	1.14
6400	4.25	1.14
6600	4.25	1.14
6800	4.26	1.13
7000	4.27	1.13
7200	4.28	1.12
7400	4.29	1.11
7600	4.30	1.11
7800	4.30	1.10
8000	4.31	1.09
8200	4.32	1.09
8400	4.33	1.09
8600	4.34	1.09
8800	4.34	1.09
9000	4.35	1.09
9200	4.36	1.10
9400	4.37	1.11
9600	4.38	1.11
10000	4.39	1.13
11000	4.43	1.14
11500	4.44	1.13
12000	4.46	1.14



ISO 9001 ISO 14001 AS 9100 CERTIFIED



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com



IF/RF MICROWAVE COMPONENTS

REV. OR
FW-4A+
211119
Page 1 of 1