

# Coaxial Fixed Attenuator

# FW-9A+

## Typical Performance Data

FREQ.	ATTENUATION	VSWR
(MHz)	(dB)	(:1)
10	8.94	1.10
20	8.94	1.10
100	8.95	1.10
200	8.96	1.10
300	8.97	1.10
400	8.98	1.10
500	8.99	1.10
600	9.00	1.10
700	9.01	1.10
800	9.02	1.10
900	9.03	1.10
1000	9.04	1.10
1200	9.05	1.10
1400	9.06	1.10
1600	9.08	1.10
1800	9.09	1.10
2000	9.11	1.10
2200	9.12	1.10
2400	9.13	1.10
2600	9.14	1.10
2800	9.16	1.10
3000	9.17	1.10
3200	9.19	1.10
3400	9.20	1.10
3600	9.21	1.10
3800	9.22	1.10
4000	9.23	1.10
4200	9.25	1.10
4400	9.26	1.10
4600	9.27	1.10
4800	9.29	1.10
5000	9.30	1.11
5200	9.32	1.11
5400	9.33	1.11
5600	9.34	1.11
5800	9.36	1.11
6000	9.37	1.11
6200	9.38	1.11
6400	9.40	1.11
6600	9.41	1.11
6800	9.42	1.10
7000	9.44	1.10
7200	9.45	1.10
7400	9.47	1.09
7600	9.48	1.09
7800	9.49	1.08
8000	9.50	1.08
8200	9.51	1.07
8400	9.53	1.07
8600	9.53	1.06
8800	9.55	1.06
9000	9.56	1.05
9200	9.56	1.05
9400	9.57	1.04
9600	9.58	1.04
10000	9.59	1.05
11000	9.62	1.08
11500	9.63	1.11
12000	9.64	1.13