

Ceramic Low Pass Filter

LF CG-92+

Typical Performance Data

FREQUENCY (MHz)	INSERTION LOSS (dB)	VSWR (:1)
10.0	0.06	1.03
20.0	0.08	1.02
50.0	0.10	1.04
100.0	0.11	1.11
150.0	0.14	1.17
200.0	0.17	1.23
250.0	0.20	1.28
300.0	0.24	1.33
350.0	0.27	1.37
400.0	0.30	1.41
450.0	0.32	1.43
500.0	0.34	1.44
550.0	0.36	1.44
600.0	0.36	1.41
650.0	0.36	1.37
700.0	0.35	1.32
750.0	0.34	1.25
800.0	0.33	1.18
850.0	0.33	1.09
900.0	0.35	1.04
950.0	0.39	1.13
990.0	0.44	1.22
1000.0	0.46	1.25
1100.0	0.68	1.52
1200.0	0.91	1.70
1300.0	1.04	1.43
1400.0	2.18	1.90
1500.0	8.83	9.15
1600.0	19.12	27.82
1700.0	32.78	46.32
1800.0	40.59	62.15
1900.0	35.35	72.27
2000.0	35.16	78.35
2200.0	38.91	90.88
2500.0	55.61	117.43
2700.0	50.94	116.94
3000.0	43.62	128.23
3200.0	42.17	128.69
3500.0	41.69	125.95
3600.0	41.76	138.23
3800.0	42.25	129.20
4000.0	43.14	130.99
4200.0	44.34	136.29
4400.0	46.14	139.09
4600.0	48.71	136.85
4800.0	52.51	145.61
5000.0	60.95	139.99



P.O. Box 350166, Brooklyn, New York 11235-0003 • Fax (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com



IF/RF MICROWAVE COMPONENTS

REV. OR
LF CG-92+
10/31/2014
Page 1 of 1