

Coaxial Low Pass Filter (Flat Time Delay)

NBLP-300

Typical Performance Data

FREQUENCY (MHz)	INSERTION LOSS (dB)	RETURN LOSS (dB)	FREQUENCY (MHz)	GROUP DELAY (nsec)
10.0	0.16	30.70	10.0	1.563
67.0	0.27	16.40	39.0	1.282
95.0	0.37	13.40	67.0	1.509
124.0	0.53	11.10	95.0	1.368
152.0	0.73	9.40	124.0	1.468
180.0	0.99	7.90	125.0	1.487
200.0	1.24	7.10	180.0	1.297
267.0	2.35	4.90	200.0	1.351
300.0	3.06	4.10	234.0	1.343
400.0	5.85	2.50	267.0	1.534
458.0	7.82	1.80	300.0	1.427
515.0	9.91	1.30	400.0	1.383
543.0	11.02	1.10	429.0	1.448
572.0	12.18	0.90	458.0	0.984
600.0	13.35	0.80	486.0	1.599
700.0	17.70	0.50	515.0	1.173
729.0	18.96	0.50	543.0	1.140
758.0	20.25	0.50	572.0	1.134
773.0	20.92	0.50	600.0	0.869
787.0	21.51	0.50	700.0	0.878
801.0	22.10	0.50	715.0	0.983
900.0	26.28	0.60	729.0	0.767
950.0	28.25	0.70	744.0	1.244
1000.0	30.16	0.80	758.0	0.807
1050.0	32.02	0.80	773.0	1.089
1100.0	33.74	0.90	787.0	1.144
1125.0	34.62	0.90	801.0	0.587
1150.0	35.50	1.00	900.0	0.940
1175.0	36.29	1.00	925.0	0.980
1200.0	37.10	1.00	950.0	0.475

REV. X1
NBLP-300
060724
Page 1 of 1



Mini-Circuits®
IF/RF MICROWAVE COMPONENTS • ISO 9001 ISO 14001 AS9100 CERTIFIED • RoHS compliant
P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661

The Design Engineers Search Engine finds the model you need, Instantly • For detailed performance specs & shopping online see

