

Fixed Attenuator

RCAT-01+

Typical Performance Data

FREQUENCY (GHz)	ATTENUATION (dB)	RETURN LOSS (dB)
0.05	1.00	53.64
0.5	1.02	36.20
1.0	1.03	29.94
1.5	1.05	26.43
2.0	1.06	23.98
2.5	1.08	22.17
3.0	1.10	20.75
3.5	1.12	19.69
4.0	1.14	18.81
4.5	1.16	18.09
5.0	1.18	17.57
5.5	1.20	17.16
6.0	1.22	16.90
6.5	1.23	16.73
7.0	1.25	16.66
7.5	1.26	16.67
8.0	1.27	16.83
8.5	1.29	17.18
9.0	1.29	17.74
9.5	1.28	18.40
10.0	1.28	19.17
10.5	1.28	20.21
11.0	1.28	21.56
11.5	1.27	23.28
12.0	1.28	25.57
12.5	1.28	28.75
13.0	1.29	31.22
13.5	1.29	28.76
14.0	1.31	25.49
14.5	1.34	22.77
15.0	1.36	20.40
15.5	1.38	18.55
16.0	1.45	17.01
16.5	1.50	15.86
17.0	1.53	14.92
17.5	1.54	13.93
18.0	1.55	13.16
18.5	1.58	12.57
19.0	1.62	12.14
19.5	1.67	11.88
20.0	1.72	11.69



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site www.minicircuits.com



The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com

IF/RF MICROWAVE COMPONENTS



REV. OR
RCAT-01+
4/24/2013
Page 1 of 1