

RF Transformer

RTX1-ED13602/1

Typical Performance Data

FREQUENCY MHz	INSERTION LOSS (dB)	RETURN LOSS (dB)
10.00	0.19	39.40
20.00	0.19	40.57
30.00	0.20	40.10
40.00	0.20	39.38
50.00	0.20	38.27
60.00	0.21	37.00
70.00	0.21	35.77
80.00	0.22	34.81
90.00	0.22	34.20
100.00	0.23	33.80
150.00	0.23	31.22
200.00	0.25	29.27
250.00	0.26	28.20
300.00	0.26	26.56
350.00	0.27	25.56
400.00	0.28	24.52
450.00	0.28	23.76
500.00	0.29	23.05
550.00	0.30	22.26
600.00	0.31	21.71
650.00	0.32	21.12
700.00	0.32	20.67
750.00	0.33	20.05
800.00	0.34	19.56
850.00	0.36	19.11
900.00	0.37	18.59
950.00	0.38	18.21
1000.00	0.40	17.64
1050.00	0.42	17.25
1100.00	0.44	16.72
1200.00	0.49	15.74
1300.00	0.55	14.70
1400.00	0.63	13.62
1500.00	0.75	12.43
1600.00	0.92	11.20
1700.00	1.16	9.88
1800.00	1.53	8.51