

Band Pass Filter

SXBP-EDU2581

Typical Performance Data

FREQUENCY (MHz)	INSERTION LOSS (dB)	RETURN LOSS (dB)	FREQUENCY (MHz)	GROUP DELAY (nsec)
0.30	86.94	0.02	5	75.48
0.60	59.37	0.03	9	27.31
1.00	38.92	0.08	12	18.93
1.25	30.61	0.15	15	16.03
2.15	22.11	0.69	18	14.09
2.60	3.32	4.45	21	13.05
2.65	2.73	5.28	24	12.49
5.00	0.48	20.08	26	12.27
23.00	0.44	25.14	29	12.13
35.00	0.49	26.90	32	12.12
65.00	1.08	17.56	35	12.22
71.50	2.14	13.10	37	12.30
73.00	3.55	7.32	39	12.46
80.50	21.16	1.31	43	12.89
84.00	31.26	1.12	48	13.80
85.00	34.57	1.08	52	15.03
89.00	54.14	1.00	55	16.34
300.00	69.48	0.75	58	17.99
500.00	73.81	1.90	59	18.62
750.00	69.96	6.46	60	19.26
1000.00	76.70	1.50	61	19.97
1500.00	62.25	1.65	63	21.59
2000.00	52.70	4.48	64	22.59
3000.00	45.72	3.36	65	23.82



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site



The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com

RF/IF MICROWAVE COMPONENTS



REV. X1
SXBP-EDU2581
URJ
170121
Page 1 of 1