


RF Transformer

TC1-1-13M-22+

Typical Performance Data

| FREQUENCY MHz | AVERAGE INSERTION LOSS (dB) | INPUT RETURN LOSS (dB) | AMPLITUDE UNBALANCE (dB) | PHASE UNBALANCE (deg.) |
|------------------|--------------------------------------|---------------------------------|--------------------------------|------------------------------|
| 50.00 | 0.19 | 33.50 | 0.56 | 0.11 |
| 100.00 | 0.24 | 29.68 | 0.55 | 0.19 |
| 500.00 | 0.46 | 19.52 | 0.45 | 0.81 |
| 1000.00 | 0.68 | 16.22 | 0.14 | 1.59 |



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com

IF/RF MICROWAVE COMPONENTS

REV. OR
TC1-1-13M-22+
6/27/2013
Page 1 of 1