

Fixed Attenuator**WR19-ATT-20+***Typical Performance Data (+25°C)*

FREQ.	ATTENUATION	WR19 INPUT VSWR	WR19 OUTPUT VSWR
(GHz)	(dB)	(:1)	(:1)
40.0	17.82	1.08	1.06
40.5	17.55	1.07	1.07
41.0	17.50	1.05	1.07
41.5	17.87	1.06	1.05
42.0	18.11	1.07	1.05
42.5	18.29	1.10	1.07
43.0	18.19	1.11	1.09
43.5	17.81	1.07	1.06
44.0	18.00	1.09	1.06
44.5	18.37	1.10	1.08
45.0	18.59	1.10	1.07
45.5	18.67	1.09	1.08
46.0	18.86	1.12	1.08
46.5	19.07	1.13	1.10
47.0	19.13	1.10	1.09
47.5	19.26	1.10	1.06
48.0	19.48	1.14	1.09
48.5	19.45	1.10	1.11
49.0	19.42	1.11	1.09
49.5	19.80	1.11	1.08
50.0	20.13	1.12	1.12
50.5	20.31	1.07	1.13
51.0	20.65	1.07	1.11
51.5	20.88	1.07	1.09
52.0	20.91	1.12	1.10
52.5	21.02	1.13	1.13
53.0	21.36	1.13	1.12
53.5	21.56	1.12	1.10
54.0	21.55	1.15	1.12
54.5	21.56	1.10	1.13
55.0	21.94	1.11	1.10
55.5	22.46	1.10	1.08
56.0	22.84	1.10	1.13
56.5	23.09	1.10	1.16
57.0	23.23	1.11	1.15
57.5	23.30	1.15	1.14
58.0	23.44	1.16	1.13
58.5	23.82	1.19	1.14
59.0	24.29	1.15	1.14
59.5	24.47	1.14	1.12
60.0	24.60	1.15	1.12



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com



IF/RF MICROWAVE COMPONENTS