

Fixed Attenuator**WR19-ATT-6+***Typical Performance Data (+25°C)*

FREQ.	ATTENUATION	WR19 INPUT VSWR	WR19 OUTPUT VSWR
(GHz)	(dB)	(:1)	(:1)
40.0	5.36	1.07	1.05
40.5	5.32	1.06	1.07
41.0	5.36	1.06	1.06
41.5	5.45	1.06	1.05
42.0	5.52	1.09	1.07
42.5	5.43	1.08	1.06
43.0	5.39	1.06	1.05
43.5	5.44	1.09	1.05
44.0	5.53	1.11	1.06
44.5	5.62	1.10	1.08
45.0	5.63	1.06	1.06
45.5	5.57	1.11	1.07
46.0	5.60	1.12	1.11
46.5	5.67	1.07	1.09
47.0	5.78	1.08	1.09
47.5	5.89	1.15	1.12
48.0	5.84	1.11	1.07
48.5	5.81	1.06	1.08
49.0	5.87	1.10	1.10
49.5	5.96	1.09	1.07
50.0	6.08	1.12	1.07
50.5	6.16	1.10	1.10
51.0	6.14	1.09	1.09
51.5	6.17	1.11	1.12
52.0	6.23	1.17	1.15
52.5	6.30	1.10	1.12
53.0	6.41	1.10	1.10
53.5	6.53	1.16	1.12
54.0	6.53	1.16	1.09
54.5	6.54	1.10	1.08
55.0	6.63	1.12	1.13
55.5	6.71	1.11	1.11
56.0	6.81	1.10	1.09
56.5	6.93	1.13	1.14
57.0	6.99	1.15	1.17
57.5	7.02	1.14	1.14
58.0	7.09	1.17	1.16
58.5	7.20	1.17	1.19
59.0	7.28	1.11	1.15
59.5	7.37	1.12	1.12
60.0	7.47	1.19	1.14



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com



IF/RF MICROWAVE COMPONENTS

REV. OR
 WR19-ATT-6+
 2/18/2026
 Page 1 of 1