

8 Way-0° Power Splitter/Combiner

ZC8PD-E18673+

Typical Performance Data

Data tested at 25DegC

FREQ. (GHz)	INSERTION LOSS ¹						AMP. UNBAL. ² (dB)	ISOLATION ³				PHASE UNBAL. ⁴ (deg.)	VSWR ⁵		
	S-1	S-2	S-3	S-4	S-5	S-8		1-2	3-4	5-6	7-8		S	1	8
18	1.3	1.5	1.5	1.3	1.3	1.5	0.37	22	22	22	22	2.6	1.13	1.13	1.12
19	1.4	1.6	1.6	1.4	1.4	1.6	0.35	29	30	30	30	2.8	1.28	1.29	1.26
20	1.4	1.6	1.6	1.4	1.4	1.6	0.36	27	27	27	27	3.0	1.14	1.21	1.19
21	1.5	1.7	1.7	1.5	1.5	1.6	0.38	23	23	23	23	2.9	1.20	1.08	1.07
22	1.5	1.7	1.7	1.5	1.5	1.7	0.36	24	24	24	24	3.1	1.15	1.09	1.07
23	1.6	1.8	1.7	1.6	1.6	1.7	0.37	29	28	29	29	3.2	1.11	1.19	1.18
24	1.6	1.8	1.8	1.6	1.6	1.8	0.39	24	25	24	24	3.5	1.11	1.16	1.15
25	1.9	2.1	2.0	1.9	1.9	2.0	0.35	41	38	38	37	3.6	1.43	1.43	1.40
26	1.9	2.0	2.1	1.8	1.8	2.0	0.40	27	27	27	26	3.6	1.35	1.34	1.31
27	1.9	2.0	2.0	1.9	1.9	2.0	0.34	26	26	26	27	3.6	1.32	1.30	1.29
28	1.9	2.1	2.1	1.9	1.9	2.1	0.36	33	34	35	35	3.8	1.39	1.23	1.23
29	1.9	2.1	2.1	1.9	1.9	2.1	0.37	25	25	25	25	4.0	1.29	1.07	1.08
30	2.0	2.1	2.1	1.9	2.0	2.1	0.39	24	25	24	24	4.0	1.24	1.08	1.08
31	2.0	2.2	2.2	2.0	2.0	2.1	0.37	30	30	31	31	4.0	1.18	1.08	1.07
32	2.0	2.2	2.2	2.0	2.0	2.2	0.33	25	25	25	25	4.2	1.07	1.10	1.10
33	2.1	2.3	2.3	2.1	2.1	2.2	0.36	29	31	29	31	4.3	1.14	1.22	1.20
34	2.2	2.4	2.4	2.2	2.2	2.3	0.35	33	33	35	33	4.5	1.14	1.31	1.30
35	2.2	2.4	2.4	2.2	2.2	2.4	0.37	27	27	27	27	4.6	1.10	1.29	1.29
36	2.3	2.5	2.5	2.3	2.3	2.4	0.34	31	32	31	32	4.7	1.13	1.33	1.33
37	2.3	2.5	2.5	2.3	2.3	2.5	0.32	26	26	26	26	5.0	1.13	1.16	1.16
38	2.5	2.7	2.6	2.5	2.5	2.6	0.33	23	23	22	23	5.1	1.32	1.20	1.22
39	2.5	2.7	2.7	2.5	2.5	2.6	0.35	28	29	28	29	5.3	1.33	1.07	1.10
40	2.5	2.7	2.7	2.5	2.5	2.7	0.37	24	24	24	24	5.4	1.30	1.17	1.19
41	2.6	2.7	2.7	2.5	2.6	2.7	0.35	27	28	27	28	5.5	1.17	1.26	1.23
42	2.6	2.8	2.8	2.6	2.6	2.7	0.34	31	32	32	33	5.6	1.10	1.38	1.35
43	2.7	2.9	2.9	2.7	2.7	2.9	0.34	28	28	28	28	5.7	1.21	1.36	1.33
44	2.7	2.9	2.9	2.7	2.7	2.9	0.33	29	30	29	30	6.0	1.11	1.31	1.31
45	2.8	3.0	2.9	2.8	2.8	2.9	0.32	27	27	28	27	6.1	1.14	1.14	1.15
46	2.8	3.0	3.0	2.8	2.9	2.9	0.34	24	25	24	25	6.2	1.09	1.10	1.11
47	2.9	3.0	3.1	2.9	2.9	3.0	0.32	33	34	33	34	6.4	1.08	1.09	1.07
48	3.0	3.1	3.1	3.0	3.0	3.1	0.32	25	25	25	24	6.5	1.09	1.09	1.08
49	3.0	3.2	3.2	3.0	3.1	3.1	0.31	25	25	24	25	6.6	1.18	1.13	1.10
50	3.1	3.2	3.3	3.1	3.1	3.2	0.32	33	34	33	34	6.8	1.11	1.12	1.12
51	3.1	3.3	3.3	3.1	3.2	3.2	0.33	25	25	26	25	6.8	1.07	1.08	1.08
52	3.3	3.4	3.4	3.3	3.3	3.4	0.32	29	29	29	29	7.1	1.18	1.19	1.16
53	3.3	3.5	3.5	3.3	3.4	3.4	0.32	33	33	32	32	7.3	1.17	1.20	1.19
54	3.4	3.5	3.6	3.4	3.4	3.5	0.31	27	27	27	26	7.4	1.20	1.12	1.15
55	3.4	3.6	3.7	3.4	3.5	3.5	0.33	35	36	37	36	7.5	1.19	1.14	1.16
56	3.5	3.7	3.7	3.5	3.5	3.6	0.35	31	30	30	29	7.7	1.15	1.06	1.08
57	3.6	3.7	3.9	3.6	3.6	3.7	0.37	27	28	27	27	7.6	1.17	1.13	1.12
58	3.6	3.8	3.9	3.6	3.7	3.7	0.37	41	40	38	38	7.9	1.09	1.06	1.08
59	3.8	3.9	3.9	3.7	3.8	3.8	0.29	27	28	27	27	7.9	1.08	1.11	1.08
60	3.8	3.9	4.0	3.7	3.8	3.9	0.36	28	29	29	29	8.3	1.09	1.04	1.07
61	3.9	4.0	4.1	3.9	3.9	4.0	0.30	41	38	39	41	8.2	1.19	1.09	1.08
62	3.9	4.1	4.1	3.9	3.9	4.0	0.34	36	35	34	35	8.3	1.13	1.06	1.09
63	4.0	4.2	4.2	4.0	4.0	4.1	0.33	40	42	43	44	8.7	1.15	1.09	1.12
64	4.2	4.3	4.3	4.1	4.2	4.2	0.32	34	34	35	33	8.7	1.24	1.13	1.10
65	4.2	4.3	4.4	4.2	4.3	4.3	0.35	35	35	34	34	9.0	1.12	1.10	1.07
66	4.3	4.4	4.4	4.2	4.3	4.3	0.35	38	36	34	36	8.9	1.11	1.14	1.08
67	4.4	4.5	4.5	4.3	4.4	4.4	0.35	41	39	37	40	9.1	1.22	1.11	1.05

1. Insertion loss is loss above theoretical loss (9dB)

2. Amplitude unbalance is average unbalance between any ports

3. Isolations are representative of all combination of ports

4. Phase unbalance is average unbalance between any ports

5. VSWR is typical representation of all ports



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site



The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com

IF/RF MICROWAVE COMPONENTS

REV. OR

ZC8PD-E18673+

12/8/2022

Page 1 of 1