# RF Transformer

T1.5-1-X65

CASE STYLE: X65

0.1 to 300 MHz


# **Maximum Ratings**

Operating Temperature	-20°C to 85°C
Storage Temperature	-55°C to 100°C
RF Power	250mW
DC Current	30mA
Permanent damage may occur if any	of these limits are exceeded

# **Pin Connections**

PRIMARY DOT	4
PRIMARY	6
SECONDARY DOT	3
SECONDARY	1
SECONDARY CT	_
NOT USED	2,5

# **Outline Drawing**



# Outline Dimensions (inch )

G	F	E	D	С	В	Α
.100	.020	.042	.010	.23	.27	.30
2.54	0.51	1.07	0.25	5.84	6.86	7.62
wt		M	L	K	J	Н
grams		.35	.300	.11	.04	.05
0.50		8.89	7.62	2.79	1.02	1 27

# Config. C PRI SEC

## **Features**

- wideband, 0.1 to 300 MHz
- excellent return loss
- also available with flat-pack (W38) & surface mount gull-wing (KK81) leads

# **Applications**

- VHF/UHF
- receivers/transmitters
- impedance matching

# **Transformer Electrical Specifications**


Ω <b>RATIO</b> (Secondary/Primary)	FREQUENCY (MHz)	3 dB MHz	INSERTION LOSS*  2 dB MHz	1 dB MHz
1.5	0.1-300	0.1-300	0.2-150	0.5-80

\* Insertion Loss is referenced to mid-band loss, 0.4 dB typ.

# **Typical Performance Data**

,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,						
JENCY II Hz)	NSERTION LOSS (dB)	INPUT R. LOSS (dB)				
10	1.96	6.70				
85	0.64	19.19				
00	0.38	23.71				
93	0.36	24.68				
35	0.42	22.20				
34	0.61	18.74				
64	0.89	14.16				
68	0.96	11.88				
29	1.03	10.26				
00	1.19	8.75				
	JENCY II 10 85 00 93 33 35 34 64 68 29	UENCY INSERTION LOSS (dB)  10 1.96 85 0.64 00 0.38 93 0.36 35 0.42 34 0.61 64 0.89 68 0.96 29 1.03				





- A. Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.

  B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.

  C. The parts covered by this specification document are subject to Mini-Circuit satandard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms.jsp