



50Ω Wideband 1.5 to 28 GHz

#### THE BIG DEAL

- · Extremely wideband, 1.5 to 28 GHz
- Very low insertion loss, 2 dB typ.
- Good return loss, 15 dB typ.
- Excellent Isolation, > 40 dB typ.



Generic photo used for illustration purposes only

Model No.	ZBT-K283+		
Case Style	VL3239		
Connectors	2.92mm Female		

# +RoHS Compliant The +Suffix identifies RoHS Compliance. See our web site for RoHS Compliance methodologies and qualifications

### **APPLICATIONS**

- · Biasing amplifiers
- · Biasing of laser diodes
- · Biasing of active antennas

### **PRODUCT OVERVIEW**

Mini-Circuits' ZBT-K283+ is an ultra-wideband MMIC coaxial bias tee covering applications from 1.5 GHz to 28 GHz with low insertion loss, excellent return loss and high DC-RF isolation over its entire frequency range. This model is capable of handling upto +30 dBm (1W) RF input power and DC input current up to 500mA.

# **KEY FEATURES**

RET FEATURES	
Feature	Advantages
Ultra-wideband, 1.5 to 28 GHz	Supports a wide range of applications with a single device, including biasing broadband amplifier, laser diodes, active antennas and more.
Low insertion loss, 2 dB	Preserves signal strength from input to output and minimizes overall system loss.
Excellent return loss, 15 dB typ.	Provides excellent matching for $50\Omega$ systems with minimal signal reflection.
RF power handling up to 1W	This model supports applications with a variety of power requirements.
Excellent DC-RF isolation > 40 dB typ, 1.5 to 28 GHz	Minimizes RF leakage and interference with other elements in the system.



### **MAXIMUM RATINGS**


Operating Temperature	-40°C to 85°C		
Storage Temperature	-55°C to 100°C		
RF Power	30 dBm max.		
Voltage at DC port	35 V max.		
Input Current	500 mA		


Permanent damage may occur if any of these limits are exceeded.

## **COAXIAL CONNECTIONS**

RF (PORT 1)	2.92mm Female
RF & DC (PORT 2)	2.92mm Female
DC (PORT 3)	(feed-through pin)
GROUND	GROUND










# OUTLINE DIMENSIONS (Inch)

Α	В	С	D	E	F	G	
.66	.86	.43	.540	.34	.190	.06	
16.7	21.8	10.8	13.72	8.5	4.83	1.5	
Н	J	K	L	M		Wt.	
.07	.22	.43	.33	.24		grams	
1 78	5.5	10.9	8.3	6.1		36	

Note: Please refer to case style drawing for details

### **ELECTRICAL SCHEMATIC**



### **ELECTRICAL SPECIFICATIONS AT 25°C**


Parameter	Frequency (MHz)	Min.	Тур.	Max.	Unit
Frequency Range		1500		28000	MHz
	1500 - 10000		1.7	2.5	dB
Insertion Loss	10000 - 20000		2.0	3.5	
Insertion Loss	20000 - 25000		2.0	3.5	
	25000 - 28000		2.2	3.7	
	1500 - 10000		57		
Isolation (RF Port to DC Port)	10000 - 20000		47		dB
isolation (RF Port to DC Port)	20000 - 25000		48		ub
	25000 - 28000		47		
Return Loss	1500 - 10000		15		
	10000 - 20000		15		dB
	20000 - 25000		13		ub
	25000 - 28000		12		
DC Resistance, DC to RF and DC port			2.7		Ohm


### **ESD RATING**

Human Body Model (HBM): Class 1B (500 V) In Accordance with ANSI/ESD STM 5.1 - 2001

### TYPICAL PERFORMANCE DATA

Frequency	Insertion Loss	VSWR (:1)		
(MHz)	(dB)	RF	RF & DC	
1500	1.3	1.59	1.59	
3000	1.1	1.30	1.13	
5000	1.2	1.46	1.28	
8000	1.3	1.07	1.17	
10000	1.5	1.19	1.25	
12000	1.5	1.37	1.31	
14000	1.3	1.26	1.20	
16000	1.3	1.23	1.27	
18000	1.8	1.78	1.84	
20000	1.9	1.84	1.93	
22000	1.7	1.43	1.61	
24000	1.8	1.38	1.56	
25000	1.8	1.36	1.52	
26000	1.8	1.28	1.44	
28000	2.0	1.21	1.35	





### NOTES

- A. Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.
- B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.
- C. The parts covered by this specification document are subject to Mini-Circuits standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the standard. Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms.jsp