

Test Cable, N-Male/N-Male

CBL-10FT-NMNM+

Typical Performance Data

FREQUENCY (MHz)	INSERTION LOSS (dB)	N-MALE 1 RETURN LOSS (dB)	N-MALE 2 RETURN LOSS (dB)
0.3	0.02	47.26	48.67
0.7	0.03	46.99	46.79
1.0	0.03	45.79	45.78
3.0	0.06	41.65	41.68
5.0	0.07	40.06	40.15
7.0	0.09	39.25	39.47
9.0	0.10	38.82	39.26
10.0	0.10	38.66	39.24
30.0	0.18	45.84	47.04
50.0	0.24	43.22	45.57
70.0	0.28	42.95	42.45
90.0	0.32	42.92	44.07
100.0	0.34	40.17	40.15
200.0	0.48	37.48	36.92
300.0	0.60	47.18	41.74
400.0	0.70	38.63	36.20
500.0	0.79	33.57	32.60
600.0	0.87	31.66	30.99
700.0	0.95	32.83	31.58
800.0	1.01	34.15	31.55
900.0	1.08	31.86	28.22
1000.0	1.14	42.41	34.33
1500.0	1.43	31.28	31.03
2000.0	1.68	30.18	34.92
2500.0	1.88	29.20	33.97
3000.0	2.11	29.22	26.54
3500.0	2.29	32.87	27.75
4000.0	2.48	28.17	25.56
4500.0	2.67	29.00	25.76
5000.0	2.82	32.96	35.76
5500.0	2.98	36.04	30.57
6000.0	3.13	28.91	31.44
6500.0	3.28	32.25	26.92
7000.0	3.44	37.12	24.95
7500.0	3.57	29.76	27.82
8000.0	3.72	30.93	25.50
8500.0	3.86	26.26	23.11
9000.0	3.96	30.42	22.14
9500.0	4.11	27.01	22.08
10000.0	4.27	25.88	22.07
11000.0	4.54	26.45	24.60
12000.0	4.71	25.85	33.57
13000.0	4.91	31.78	31.03
14000.0	5.23	36.02	21.06
15000.0	5.42	27.89	24.30
16000.0	5.68	28.78	33.27
17000.0	5.90	26.01	32.89
18000.0	6.29	22.48	26.18



ISO 9001 ISO 14001 AS 9100 CERTIFIED

P.O. Box 350186, Brooklyn, New York 11235-0000 (718) 934-4500 Fax (718) 332-4851 For detailed performance specs & shopping online see Mini-Circuits web site



The Design Engineers Search Engine Provides ACTUAL Data Instantly From MIN-CIRCUITS At: www.minicircuits.com

RF/MICROWAVE COMPONENTS



REV. X1

CBL-10FT-NMNM+

12/23/2008

Page 1 of 1