

Right Angle Adapter, 2.92mm Male to 2.4mm Female KMR-24F+

Typical Performance Data

FREQUENCY (GHz)	INSERTION LOSS (dB)	2.92mm-MALE VSWR (:1)	2.4mm-FEMALE VSWR (:1)
0.01	0.01	1.01	1.01
0.05	0.01	1.00	1.00
0.1	0.01	1.01	1.00
0.2	0.02	1.01	1.01
0.3	0.02	1.01	1.01
0.4	0.03	1.01	1.01
0.5	0.03	1.01	1.02
0.6	0.04	1.01	1.02
0.7	0.04	1.02	1.02
0.8	0.04	1.02	1.02
0.9	0.05	1.02	1.02
1.0	0.05	1.02	1.02
2.0	0.07	1.01	1.02
3.0	0.10	1.02	1.01
4.0	0.13	1.05	1.04
5.0	0.14	1.08	1.08
6.0	0.14	1.11	1.11
7.0	0.13	1.11	1.11
8.0	0.13	1.10	1.09
9.0	0.13	1.08	1.05
10.0	0.13	1.06	1.03
11.0	0.13	1.04	1.02
12.0	0.13	1.04	1.02
13.0	0.13	1.04	1.03
14.0	0.14	1.05	1.03
15.0	0.14	1.06	1.01
16.0	0.14	1.06	1.02
17.0	0.15	1.04	1.05
18.0	0.15	1.02	1.05
19.0	0.16	1.03	1.03
20.0	0.17	1.07	1.03
21.0	0.18	1.12	1.10
22.0	0.20	1.15	1.16
23.0	0.20	1.15	1.16
24.0	0.20	1.11	1.11
25.0	0.18	1.05	1.03
26.0	0.19	1.04	1.06
28.0	0.22	1.16	1.19
30.0	0.24	1.18	1.12
32.0	0.24	1.15	1.13
34.0	0.23	1.00	1.13
36.0	0.27	1.18	1.11
38.0	0.24	1.18	1.14
40.0	0.21	1.06	1.07
42.0	0.21	1.17	1.07
43.0	0.21	1.20	1.04
43.5	0.21	1.20	1.02



P.O. Box 350166, Brooklyn, New York 11235-0003 • (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com



IF/RF MICROWAVE COMPONENTS

REV. OR
 KMR-24F+
 11/6/2019
 Page 1 of 1