RF Transformer

0.08 to 200 MHz

T1-1T-38+



Generic photo used for illustration purposes only CASE STYLE: W38

+RoHS Compliant

The +Suffix identifies RoHS Compliance. See our web site for RoHS Compliance methodologies and qualifications


Maximum Ratings

Operating Temperature	-20°C to 85°C			
Storage Temperature	-55°C to 100°C			
RF Power	0.25W			
DC Current	30mA			
Demonstrate demons many season if any of these limits are				


Pin Connections

PRIMARY DOT	4
PRIMARY	6
SECONDARY DOT	3
SECONDARY	1
SECONDARY CT	2
NOT USED	5

Outline Drawing




NOTE: PIN NUMBERS DO NOT APPEAR ON UNIT, FOR REFERENCE ONLY. INDEX MARK NEAR PIN 6.



Outline Dimensions (inch)

. 020	. 042	. 010	. 23	. 27	. 30 7.62
0.51	1.07	0.25	5.84	6.86	
wt	L	K	J	H	G
grams	. 036	. 31	. 09	. 05	. 100
0.50	0.91	7.87	2.29	1.27	2.54

Config. A



Features

• excellent return loss

• wideband, 0.08 to 200 MHz

Applications

- receivers/transmitters

Transformer Electrical Specifications


Ω RATIO	FREQUENCY (MHz)	INSERTION LOSS*		
		3 dB MHz	2 dB MHz	1 dB MHz
1	0.08-200	.08-200	0.15-150	0.2-80

^{*}Insertion Loss is referenced to mid-band loss, 0.3 dB typ.

Typical Performance Data

	FREQUENCY (MHz)	INSERTION LOSS (dB)	INPUT R. LOSS (dB)	
1	0.05	2.78	1.64	
	0.08	1.18	4.39	
	0.20	0.52	9.45	
	0.50	0.38	16.31	
	1.00	0.36	19.67	
	80.00	0.64	9.96	
	99.33	0.76	8.80	
	150.00	1.23	5.83	
	192.51	1.60	4.60	
	200.00	1.63	4.55	





- A. Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.

 B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.

 C. The parts covered by this specification document are subject to Mini-Circuit satandard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms.jsp