

# Wideband Amplifier

# ZVA-183+

## Typical Performance Data

FREQUENCY (MHz)	GAIN (dB) 12V	DIRECTIVITY (dB) 12V	VSWR IN (:1) 12V	VSWR OUT (:1) 12V	NOISE FIGURE (dB) 12V	Pout at 1dB Comp. (dBm) 12V	Output IP3 (dBm) 12V
700.0	26.25	49.93	1.50	1.74	4.84	23.77	36.01
800.0	26.32	49.16	1.47	1.64	4.74	23.89	36.82
900.0	26.40	50.96	1.43	1.58	4.68	23.80	37.38
1000.0	26.45	49.60	1.40	1.53	4.66	23.67	37.33
2000.0	26.83	49.44	1.27	1.28	3.91	23.95	36.86
3000.0	26.88	54.76	1.24	1.07	3.46	24.39	36.24
4000.0	26.87	50.02	1.23	1.21	3.19	24.80	35.58
5000.0	26.75	50.10	1.23	1.41	2.89	25.08	35.10
6000.0	26.68	47.03	1.26	1.46	2.74	25.04	34.38
7000.0	26.64	49.03	1.30	1.35	2.56	25.43	33.78
8000.0	26.53	52.49	1.34	1.17	2.49	25.34	33.26
9000.0	26.42	59.55	1.36	1.19	2.48	25.23	32.62
10000.0	26.23	53.89	1.36	1.39	2.63	25.09	32.09
11000.0	26.12	54.33	1.38	1.52	2.87	24.73	31.27
12000.0	26.28	38.47	1.37	1.37	3.25	24.14	30.49
13000.0	26.27	56.13	1.37	1.02	3.33	23.68	30.47
14000.0	26.03	43.11	1.40	1.38	3.14	23.31	30.19
15000.0	26.04	44.40	1.34	1.55	3.31	23.24	29.63
16000.0	26.21	34.69	1.12	1.36	3.26	23.06	29.01
17000.0	25.90	33.52	1.08	1.01	3.41	22.76	28.88
18000.0	25.12	37.12	1.16	1.37	3.72	21.65	28.98



ISO 9001 ISO 14001 AS 9100 CERTIFIED

P.O. Box 350188, Brooklyn, New York 11235-0000 (718) 934-4500 Fax (718) 352-4951 For detailed performance specs & shopping online see Mini-Circuits web site



The Design Engineers Search Engine Provides ACTUAL Data Instantly From MIN-CIRCUITS At: [www.minicircuits.com](http://www.minicircuits.com)

RF/MW MICROWAVE COMPONENTS



REV. X1  
ZVA-183+  
12/22/2008  
Page 1 of 1