

# Coaxial Band Pass Filter

# VBF-1560+

## Typical Performance Data

FREQUENCY (MHz)	INSERTION LOSS (dB)	RETURN LOSS (dB)
50	71.05	0.09
200	60.45	0.20
500	47.20	0.32
1040	34.41	0.66
1100	28.83	0.77
1250	15.98	1.53
1340	8.27	3.81
1400	4.51	9.06
1500	2.68	31.86
1560	2.61	23.39
1620	2.83	15.32
1780	4.36	16.94
1850	8.85	6.51
1910	15.74	3.74
2000	27.66	2.68
2100	41.90	2.13
2105	41.62	2.09
3500	28.55	0.35
4200	36.01	0.45

REV. X1  
VBF-1560+  
080220  
Page 1 of 1



IF/RF MICROWAVE COMPONENTS • ISO 9001 ISO 14001 AS 9100 CERTIFIED RoHS compliant  
P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661



The Design Engineers Search Engine finds the model you need, Instantly • For detailed performance specs & shopping online see

