

# Coaxial SMA Band Pass Filter

# VBFZ-780-S+

## Typical Performance Data

FREQUENCY (MHz)	INSERTION LOSS (dB)	RETURN LOSS (dB)
10	79.73	0.00
80	65.09	0.01
250	57.62	0.07
440	33.58	0.43
460	29.32	0.52
510	19.74	0.90
542	14.25	1.40
595	6.78	3.73
643	3.19	8.79
710	1.87	15.24
780	1.76	13.38
850	2.01	10.41
1052	3.95	9.09
1105	7.91	5.42
1158	15.43	3.30
1300	30.97	1.24
1320	31.84	1.13
3000	76.71	0.26
8000	47.70	1.95
16000	45.21	0.90

REV. OR  
VBFZ-780-S+  
200808  
Page 1 of 1



IF/RF MICROWAVE COMPONENTS • ISO 9001 ISO 14001 AS 9100 CERTIFIED RoHS compliant  
P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661



The Design Engineers Search Engine finds the model you need, Instantly • For detailed performance specs & shopping online see

