

Typical Performance Data

| FREQUENCY (MHz) | AVERAGE INSERTION LOSS (dB) | INPUT RETURN LOSS (dB) | AMPLITUDE UNBALANCE (dB) | PHASE UNBALANCE (deg) |
|--------------------|--------------------------------------|---------------------------------|--------------------------------|-----------------------------|
| 6 | 0.86 | 12.61 | 0.00 | 0.01 |
| 10 | 0.77 | 16.33 | 0.00 | 0.04 |
| 50 | 0.54 | 24.74 | 0.00 | 0.09 |
| 100 | 0.52 | 26.69 | 0.02 | 0.29 |
| 150 | 0.53 | 25.75 | 0.04 | 0.37 |
| 275 | 0.58 | 20.40 | 0.16 | 1.00 |
| 350 | 0.63 | 17.49 | 0.25 | 1.59 |
| 425 | 0.75 | 14.94 | 0.33 | 2.45 |
| 500 | 0.91 | 12.72 | 0.44 | 3.89 |
| 625 | 1.63 | 9.71 | 0.54 | 7.70 |