

# Coaxial SMA Band Pass Filter

# VBFZ-1065-S+

## Typical Performance Data

FREQUENCY (MHz)	INSERTION LOSS (dB)	RETURN LOSS (dB)
10	81.73	0.00
80	66.51	0.01
250	58.37	0.05
600	30.82	0.43
630	26.53	0.53
723	14.55	1.16
792	7.33	2.94
850	3.78	6.53
980	1.80	15.88
1065	1.68	16.44
1150	1.83	13.40
1275	2.30	10.35
1435	3.06	20.10
1520	6.46	6.22
1605	13.53	3.44
1760	27.72	2.42
1800	33.65	2.05
3000	70.36	0.76
8000	46.84	0.67
11000	46.55	0.95

REV. OR  
VBFZ-1065-S+  
200808  
Page 1 of 1



IF/RF MICROWAVE COMPONENTS • ISO 9001 ISO 14001 AS 9100 CERTIFIED RoHS compliant  
P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661



The Design Engineers Search Engine finds the model you need, Instantly • For detailed performance specs & shopping online see

