

## Typical Performance Data

FREQUENCY (MHz)	AVERAGE INSERTION LOSS (dB)	INPUT RETURN LOSS (dB)	AMPLITUDE UNBALANCE (dB)	PHASE UNBALANCE (deg)
8	0.74	14.43	0.00	0.06
10	0.72	15.42	0.01	0.06
16	0.65	16.83	0.00	0.03
59	0.54	18.72	0.01	0.14
100	0.56	17.66	0.03	0.00
200	0.79	14.80	0.13	0.11
300	1.02	12.34	0.33	0.51
400	1.05	10.45	0.66	1.24
500	1.09	9.00	1.10	2.48
600	1.13	7.78	1.78	4.22